

PRO 3000

Generating set

INVERTER PRO PORTABLE POWER
GENERATING SET.



1 Is the fuel level high enough?

yes
go to question 2.



no
Using a funnel and a jerrican, fill with fuel. Make sure that the filter stays in place during this operation!



2 Is the switch in the ON position, is the petrol tap open?

yes
go to question 3.



no
Set the switch to ON and open the tap.



3 Is the battery connected, with the + and - terminals the correct way round?

yes
go to question 4.



no
Connect the battery with the correct polarity. Check that the battery contains acid. Turn the key.



@PRO 3000

Generating set

INVERTER PRO PORTABLE POWER
GENERATING SET.



4 Is there enough oil in the engine?

yes

go to question 5.



no

With a funnel, add oil up to the mark indicated on the casing.



5 Is the spark plug in good working order?

yes

go to question 6.



no

Use a spark plug wrench to replace the spark plug.



6 Does the petrol reach the carburettor?

yes

your genset
is ready for
start-up.

no

Check using a flat screwdriver. If the petrol does not reach the carburettor,
return your genset to the ASS.

