

# KOHLER®

# SDMO®



## HX 3000 C

PORTABLE POWER

Generating Sets Range INTENS

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

### Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



## HX 3000 C

### GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	2.70
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	1.30
75% Autonomy (h) *	2.40
Sound power level guaranteed LwA dB(A)	98
Acoustic pressure level @1m in dB(A)	84
Acoustic pressure level @7m in dB(A)	69

### ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX200
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	196
Oil system capacity including filters (L)	0.60

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	41

### PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	43
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	661

**KOHLER®**  
**SDMO®**

2/18/2020

HX 3000 C - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

### ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

### OPTIONS



**R01** This set includes the hour meter and the differential circuit breaker.



**R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



**R06** Trolley kit for 2 and 3 kW generating sets.



**RBH1** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



**RBH0-5** Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



**RHO** Cover for SDMO 's generating sets, welding sets and water pumps



**RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



**RPQ** For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable.