



## DIESEL 10000 A SILENCE AVR

PORTABLE POWER

GENERATING SET Range DIESEL SILENCE

### PRODUCT ADVANTAGES

- Generating set guaranteed 3 years
- KOHLER air-cooled industrial engine
- AVR: Automatic Voltage Regulation
- Connection interface equipped with an hour meter
- Hydrocarbons bulk tank

GENERATOR SMART CARE is a Bluetooth box which can be used on all the brand's portable generators. TECHNOLOGY EQUIPPED WITH AN INNOVATIVE APPLICATION Generator Smart Care is a digital solution which provides access to:- The list of generators- The maintenance due dates- A maintenance aid- The map of reseller partners The APM202 control panel displays overspeed, starting failure, oil pressure, battery and temperature

### Range DIESEL SILENCE

Both long run times and very long life for professional applications.



# DIESEL 10000 A SILENCE AVR

## GENERAL SPECIFICATIONS

Range	DIESEL SILENCE
Frequency (Hz)	50 Hz
Max power (kW) *	8.80
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	27
75% cons. (l/h) *	2.10
75% Autonomy (h) *	12.90
Sound power level guaranteed LwA dB(A)	97
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	68

## ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	KD425-2
Distribution	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm3)	851
Oil system capacity including filters (l)	2.60

## ALTERNATOR SPECIFICATIONS

Technology	Collar and brush
AVR Regulation	Yes
Indication of protection	IP 23
Insulation class	H

## PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker + hour meter + indicator + APM202

## DIMENSIONS AND WEIGHT

Length (cm)	118.30
Width (cm)	67.30
Height (cm)	96
Dry Weight (kg)	269

## PACKAGING

Packaging type	Box
Length (cm)	120
Width (cm)	69
Height (cm)	94
Weight (kg)	272
Pallet type	
Number of box by pallet	0
Pallet height (cm)	0
weight of the packaged Pallet (kg)	0




4/21/2021

DIESEL 10000 A SILENCE AVR - PORTABLE POWER - GENERATING SET DIESEL SILENCE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com



4/21/2021

DIESEL 10000 A SILENCE AVR - PORTABLE POWER - GENERATING SET DIESEL SILENCE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - [www.kohlersdmo.com](http://www.kohlersdmo.com)

## DIESEL 10000 A SILENCE AVR


### ACCESSORIES SUPPLIED



User and maintenance manual



Battery without maintenance



Lifting eye

Hour meter

### OPTIONS



**R02B** This set includes a differential switch, a hour meter, the plugs and a thermal circuit breaker.



**RSTART2** Remote control in order to start or stop the generating set until a distance of 50 meters (needs the APM202 control panel)



**VERS050** Switches over automatically if the mains fails, 40A or 100A 1P or if the mains fails, 25A or 40A 3P (needs the installation of a APM202 control panel). Includes the battery charger.



**R05M** The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



**RKDS3** Maintenance kit for KOHLER KD425-2 engine.



**RAP** The adaptor for industrial sockets is used to connect 230-V appliances to the industrial socket.



**RPM** Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V