

KOHLER®

SDMO®



HX 2500 UK

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HX 2500 UK

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	1.90
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	3.10
75% cons. (l/h) *	0.90
75% Autonomy (h) *	3.40
Sound power level guaranteed LwA dB(A)	94
Acoustic pressure level @1m in dB(A)	80
Acoustic pressure level @7m in dB(A)	65

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX160
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	163
Oil system capacity including filters (L)	0.60

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 115V 16A socket - circuit breaker + 1 230V 16A socket - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	39

PACKAGING

Packaging type	Box
Length (cm)	60.50
Width (cm)	46
Height (cm)	44
Weight (kg)	41
Pallet type	140/110
Number of box by pallet	15
Pallet height (cm)	145
weight of the packaged Pallet (kg)	631

KOHLER®
SDMO®

7/22/2019

HX 2500 UK - PORTABLE POWER - Generating Sets INTENS

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R18 Maintenance kit for Honda GX160 and GX200 engine (except Alizé 3000)



R50 16A blue 230V male plug - Sold per 1 or 10



R51 16A yellow 115V male plug - Sold per 1 or 10



R54 Adaptator R54 16A/13A adaptor unit. Sold per 1 or 3



R55 ADAPTATOR R55 16A/13A adaptor economy. Sold per 1 or 3



R56 ADAPTATOR R56 16A/13A double adaptor. Sold per 1 or 3



RBH1 Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5 Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RHO Cover for SDMO's generating sets, welding sets and water pumps