# **GENERATING SET PHOENIX 2800**





## **GENERAL SPECIFICATIONS**

Max power (kW) *	2.80
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	4.10
75% Autonomy (h) *	3.20
Sound power level guaranteed LwA dB(A)	96
Acoustic pressure level @7m in dB(A)	67

# **ENGINE SPECIFICATIONS**

Engine brand	KOHLER
Start	Starter
Displacement (cm3)	208
Oil system capacity including filters	0.60

#### **PRODUCT ADVANTAGES**

- · Good value for money
- Entire group guaranteed 2 years or 1000 hours
- Made in France

# **ALTERNATOR SPECIFICATIONS**

Indication of protection	IP 23
Insulation class	Н

#### Range PHOENIX

Ease the gardening and DIY far from electric sockets.

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker













Length (cm)	59
Width (cm)	46
Height (cm)	43
Dry Weight (kg)	42

#### **OPTIONS**

- RKBP1
- R30
- RHO



## Can I use my generator:





